

Compilazione regolamento di esercizio: Informazioni utili



Modello dell'inverter	Icc (A)	DDI				SPI			
		Marca	Modello	CEI EN	Interblocchi	Marca	Modello	FW	
SB 1.5-1 VL-40	9	Zettler Electronics	AZ733W-2A-12DE	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	6.0
SB 2.0-1 VL-40	11	Zettler Electronics	AZ733W-2A-12DE	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	6.0
SB 2.5-1 VL-40	13	Zettler Electronics	AZ733W-2A-12DE	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	6.0
SB 3.0-1AV-41	16	FUJITSU	FTR-K3 AB012W-PS	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	1.1
SB 3.6-1AV-41	19	FUJITSU	FTR-K3 AB012W-PS	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	1.1
SB 4.0-1AV-41	21	FUJITSU	FTR-K3 AB012W-PS	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	1.1
SB 5.0-1AV-41	24	FUJITSU	FTR-K3 AB012W-PS	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	1.1
SB 6.0-1AV-41	27,5	FUJITSU	FTR-K3 AB012W-PS	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	1.1
STP3.0-3AV-40	7,55	FUJITSU	FTR-K3 AB012W-PS	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	2.13
STP4.0-3AV-40	9,06	FUJITSU	FTR-K3 AB012W-PS	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	2.13
STP5.0-3AV-40	10,41	FUJITSU	FTR-K3 AB012W-PS	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	2.13
STP6.0-3AV-40	11,47	FUJITSU	FTR-K3 AB012W-PS	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	2.13
STP8.0-3AV-40	11,9	Hongfa	HF161-W/12-HT(704) 12V 277Vac 26A 1A 2,26mm	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	1.1
STP10.0-3AV-40	14,83	Hongfa	HF161-W/12-HT(704) 12V 277Vac 26A 1A 2,26mm	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	1.1
STP 15000TL-30	30,31								
STP 20000TL-30	31,07								
STP 25000TL-30	40,06								
STP 50-40	85,91								
STP 60-10	106,6								
SHP 75-10	128,4								
SHP 100-20	166,39								
STP 110-60	175								
SHP 150-20	170,34								
SBS 2.5-1 VL-10	13	Zettler Electronics	AZ733W-2A-12DE	Relé	EN61810-1	no	SMA Solar Technology AG	SMA Grid Guard	6.0
SBS 3.7-10	20	Panasonic	AHES3191	Relé	EN61810-2	no	SMA Solar Technology AG	SMA Grid Guard	6.0
SBS 5.0-10	28	Panasonic	AHES3191	Relé	EN61810-3	no	SMA Solar Technology AG	SMA Grid Guard	6.0
SBS 6.0-10	32	Panasonic	AHES3191	Relé	EN61810-4	no	SMA Solar Technology AG	SMA Grid Guard	6.0
STPS 60-10	128,4								

Modello dell'inverter	N° poli	Potenza Nominale AC [watt]	cosp nominale	Tensione Nominale	Rapporto Icc/In
SB 1.5-1 VL-40	1P+N	1500	1	230 V	1,29
SB 2.0-1 VL-40	1P+N	2000	1	230 V	1,22
SB 2.5-1 VL-40	1P+N	2500	1	230 V	1,18
SB 3.0-1AV-41	1P+N	3000	1	230 V	1,23
SB 3.6-1AV-41	1P+N	3680	1	230 V	1,19
SB 4.0-1AV-41	1P+N	4000	1	230 V	1,21
SB 5.0-1AV-41	1P+N	5000	1	230 V	1,20
SB 6.0-1AV-41	1P+N	6000	1	230 V	1,20
STP3.0-3AV-40	3P+N	3000	1	230 V / 400 V	1,68
STP4.0-3AV-40	3P+N	4000	1	230 V / 400 V	1,56
STP5.0-3AV-40	3P+N	5000	1	230 V / 400 V	1,37
STP6.0-3AV-40	3P+N	6000	1	230 V / 400 V	1,26
STP8.0-3AV-40	3P+N	8000	1	230 V / 400 V	1,03
STP10.0-3AV-40	3P+N	10000	1	230 V / 400 V	1,02
STP 15000TL-30	3P+N	15000	1	230 V / 400 V	1,4
STP 20000TL-30	3P+N	20000	1	230 V / 400 V	1,07
STP 25000TL-30	3P+N	25000	1	230 V / 400 V	1,11
STP 50-40	3P+N	50000	1	230 V / 400 V	1,18
STP 60-10	3P	60000	1	230 V / 400 V	1,23
SHP 75-10	3P	75000	1	230 V / 400 V	1,18
SHP 100-20	3P	100000	1	230 V / 400 V	1,15
STP 110-60	3P	110000	1	230 V / 400 V	1,1
SHP 150-20	3P	150000	1	230 V / 400 V	1,17
SBS 2.5-1 VL-10	1P+N	2500	1	230 V	1,18
SBS 3.7-10	1P+N	3680	1	230 V	1,25
SBS 5.0-10	1P+N	5000	1	230 V	1,29
SBS 6.0-10	1P+N	6000	1	230 V	1,23
STPS 60-10	3P	75000	1	230 V / 400 V	1,18